

AC TUBULAR MOTORS

FDT - 35 - R


R:Radio

Mechanical Limit + Built-in Receiver + Dot-Move & Light Adjust Functions




- ◆ Mechanical limit Switch
- ◆ Quite Design tubular motor
- ◆ Very Easy to Install and Operate
- ◆ \varnothing 35 mm diameter
- ◆ 230V AC motor
- ◆ Powerful motor capacity


Use



Dimension Drawing



Inner Structure Picture



Motor Type Explanation

FDT - **35** - **R** - **6** / **28**
 Fox Domotics Tubular Tube Diameter Radio Rated Torque(Nm) Output Speed(rpm)

Technical Data	Rated Torque (Nm)	Out put Speed (rpm)	Tube Diameter (mm)	Rated Voltage (V)	Frequency (Hz)	Rated Power (W)	Rated Current (A)	Continuous Running Time (min)	Protection Degree (IP)	Max Limit Turns (turn)	L1 / L2 (mm)	
230V / 50Hz												
FDT-35-R Radio	FDT-35-R - 6/28	6	28	35	230	50	121	0.53	4	IP44	30	577/564



Product Certificate